

FORM PTO-1390
(REV 11-98)

U.S. DEPARTMENT OF COMMERCE PATENT AND TRADEMARK OFFICE

ATTORNEY'S DOCKET NUMBER

3815.91

**TRANSMITTAL LETTER TO THE UNITED STATES
DESIGNATED/ELECTED OFFICE (DO/EO/US)
CONCERNING A FILING UNDER 35 U.S.C. 371**

U.S. APPLICATION NO. (If known, see 37 CFR 1.5)

09/446560
To be assignedINTERNATIONAL APPLICATION NO.
PCT/JP99/02154INTERNATIONAL FILING DATE
April 22, 1999PRIORITY DATE CLAIMED
April 23, 1998

TITLE OF INVENTION

CDMA RECEIVER AND CDMA TRANSCEIVER

APPLICANT(S) FOR DO/EO/US

Sadayuki Abeta, Mamoru Sawahashi and Fumiyuki Adachi

Applicant herewith submits to the United States Designated/Elected Office (DO/EO/US) the following items and other information:

1. ☒ This is a **FIRST** submission of items concerning a filing under 35 U.S.C. 371.
2. ☐ This is a **SECOND** or **SUBSEQUENT** submission of items concerning a filing under 35 U.S.C. 371.
3. ☒ This express request to begin national examination procedures (35 U.S.C. 371(f)) at any time rather than delay examination until the expiration of the applicable time limit set in 35 U.S.C. 371(b) and PCT Articles 22 and 39(1).
4. ☐ A proper Demand for International Preliminary Examination was made by the 19th month from the earliest claimed priority date.
5. ☒ A copy of the International Application as filed (35 U.S.C. 371(c)(2))
 - a. ☐ is transmitted herewith (required only if not transmitted by the International Bureau).
 - b. ☒ has been transmitted by the International Bureau.
 - c. ☐ is not required, as the application was filed in the United States Receiving Office (RO/US).
6. ☒ A translation of the International Application into English (35 U.S.C. 371(c)(2)).
7. ☒ Amendments to the claims of the International Application under PCT Article 19 (35 U.S.C. 371(c)(3))
 - a. ☐ are transmitted herewith (required only if not transmitted by the International Bureau).
 - b. ☐ have been transmitted by the International Bureau.
 - c. ☐ have not been made; however, the time limit for making such amendments has NOT expired.
 - d. ☒ have not been made and will not be made.
8. ☐ A translation of the amendments to the claims under PCT Article 19 (35 U.S.C. 371(c)(3)).
9. ☒ An oath or declaration of the inventor(s) (35 U.S.C. 371(c)(4)).
10. ☐ A translation of the annexes to the International Preliminary Examination Report under PCT Article 36 (35 U.S.C. 371(c)(5)).

Items 11. to 16. below concern document(s) or information included:

11. ☐ An Information Disclosure Statement under 37 CFR 1.97 and 1.98.
12. ☒ An assignment document for recording. A separate cover sheet in compliance with 37 CFR 3.28 and 3.31 is included.
13. ☒ A FIRST preliminary amendment.
☐ A SECOND or SUBSEQUENT preliminary amendment.
14. ☐ A substitute specification.
15. ☐ A change of power of attorney and/or address letter.
16. ☐ Other items or information:

U.S. APPLICATION NO. (if known see 37 CFR 1.53) 09/446560		INTERNATIONAL APPLICATION NO. PCT/JP99/02154		ATTORNEY'S DOCKET NUMBER 3815.91	
17. <input checked="" type="checkbox"/> The following fees are submitted: BASIC NATIONAL FEE (37 CFR 1.492 (a) (1) - (5)) : Neither international preliminary examination fee (37 CFR 1.482) nor international search fee (37 CFR 1.445(a)(2)) paid to USPTO and International Search Report not prepared by the EPO or JPO \$970.00 International preliminary examination fee (37 CFR 1.482) not paid to USPTO but International Search Report prepared by the EPO or JPO \$840.00 International preliminary examination fee (37 CFR 1.482) not paid to USPTO but international search fee (37 CFR 1.445(a)(2)) paid to USPTO \$760.00 International preliminary examination fee paid to USPTO (37 CFR 1.482) but all claims did not satisfy provisions of PCT Article 33(1)-(4) \$670.00 International preliminary examination fee paid to USPTO (37 CFR 1.482) and all claims satisfied provisions of PCT Article 33(1)-(4) \$96.00 ENTER APPROPRIATE BASIC FEE AMOUNT =				CALCULATIONS PTO USE ONLY	
Surcharge of \$130.00 for furnishing the oath or declaration later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 months from the earliest claimed priority date (37 CFR 1.492(e)).					
CLAIMS	NUMBER FILED	NUMBER EXTRA	RATE		
Total claims	19 - 20 =	0	X \$18.00	\$	
Independent claims	6 - 3 =	3	X \$78.00	\$	234
MULTIPLE DEPENDENT CLAIM(S) (if applicable)			+ \$260.00	\$	
TOTAL OF ABOVE CALCULATIONS =				\$	1,074
Reduction of 1/2 for filing by small entity, if applicable. A Small Entity Statement must also be filed (Note 37 CFR 1.9, 1.27, 1.28).				\$	
SUBTOTAL =				\$	1,074
Processing fee of \$130.00 for furnishing the English translation later than <input type="checkbox"/> 20 <input type="checkbox"/> 30 months from the earliest claimed priority date (37 CFR 1.492(f)).				\$	
TOTAL NATIONAL FEE =				\$	
Fee for recording the enclosed assignment (37 CFR 1.21(h)). The assignment must be accompanied by an appropriate cover sheet (37 CFR 3.28, 3.31). \$40.00 per property				\$	
TOTAL FEES ENCLOSED =				\$	1,074
				Amount to be:	\$
				refunded	\$
				charged	\$

- a. ☒ A check in the amount of \$ 1,074 to cover the above fees is enclosed.
- b. ☐ Please charge my Deposit Account No. _____ in the amount of \$ _____ to cover the above fees.
A duplicate copy of this sheet is enclosed.
- c. ☒ The Commissioner is hereby authorized to charge any additional fees which may be required, or credit any
overpayment to Deposit Account No. 02-4270. A duplicate copy of this sheet is enclosed.

NOTE: Where an appropriate time limit under 37 CFR 1.494 or 1.495 has not been met, a petition to revive (37 CFR 1.137(a) or (b)) must be filed and granted to restore the application to pending status.

SEND ALL CORRESPONDENCE TO

Brown Raysman Millstein Felder & Steiner LLP
 120 West 45th Street
 New York, NY 10036



SIGNATURE.

Larry Liberchuk

NAME

40,352

REGISTRATION NUMBER

IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

Applicants: Sadayuki Abeta, et al.
Int'l. Appl. No.: PCT/JP99/02154
Int'l. Filing Date: April 22, 1999
U.S. Serial No.: To be assigned
Filing Date: Concurrently herewith
Title: CDMA RECEIVER AND CDMA TRANSCEIVER

Assistant Commissioner for Patents
Washington, D.C. 20231

PRELIMINARY AMENDMENT

Sir:

Concurrently with the filing of the above-referenced application and prior to the substantive examination thereof, please amend the above-referenced application as follows:

IN THE SPECIFICATION

Page 12:

lines 22-23, delete "any one of claims 1-4" and insert --claim 1-- therefor.

Page 13:

lines 4-5, delete "any one of claims 1-5" and insert --claim 1-- therefor;

lines 8-9, delete "any one of claims 1-6" and insert --claim 1-- therefor.

Page 15:

lines 12-13, delete "any one of claims 8-11" and insert --claim 8-- therefor;

lines 21-22, delete "any one of claims 8-12" and insert --claim 8-- therefor;

Page 16:

lines 4-5, delete "any one of claims 8-13" and insert --claim 8-- therefor;

lines 12-13, delete "any one of claims 8-14" and insert --claim 8-- therefor.

IN THE CLAIMS

Please amend claims 5-7 and 12-15 as follows:

In Claim 5:

lines 1-2, delete "any one of claims 1-4" and insert --claim 1-- therefor.

In Claim 6:

lines 1-2, delete "any one of claims 1-5" and insert --claim 1-- therefor.

In Claim 7:

lines 1-2, delete "any one of claims 1-6" and insert --claim 1-- therefor.

In Claim 12:

lines 1-2, delete "any one of claims 8-11" and insert --claim 8-- therefor.

In Claim 13:

lines 1-2, delete "any one of claims 8-12" and insert --claim 8-- therefor.

In Claim 14:

lines 1-2, delete "any one of claims 8-13" and insert --claim 8-- therefor.

In Claim 15:

lines 1-2, delete "any one of claims 8-14" and insert --claim 8-- therefor.

REMARKS

After entry of this amendment to eliminate multiple dependency claims, it is believed that the above-referenced application is ready for substantive examination by the Examiner. Early and favorable examination thereof is, therefore, respectfully requested.

In the event that additional cooperation in this case may be helpful to complete its prosecution, the Examiner is cordially invited to contact Applicants' representative at the telephone number listed below.

The Commissioner is hereby authorized to charge any insufficient fees or credit any overpayment associated with the above-identified application to Deposit Account No. 02-4270.

Respectfully submitted,

Dated: December 22, 1999



Larry Liberchuk
Reg. No. 40,352
Attorney for Applicants
BROWN RAYSMAN MILLSTEIN FELDER
& STEINER LLP
120 West Forty-Fifth Street
New York, New York 10036
(212) 944-1515

SPECIFICATION

27/12/99

TITLE OF THE INVENTION

CDMA RECEIVER AND CDMA TRANSCEIVER

5

TECHNICAL FIELD

The present invention relates to a CDMA (Code Division Multiple Access) receiver and a CDMA transceiver which have high resistance to fading fluctuations, and carry out highly accurate channel estimation, considering the rate of channel fluctuations (propagation path fluctuations).

BACKGROUND ART

In a mobile communication environment, fluctuations in amplitude and phase can take place in a propagation channel because of Rayleigh fading caused by variations in relative locations of a mobile station and a base station. Therefore, it is common for a conventional phase modulation method which transmits data (information) by carrier phase to impose data on relative phases of successive symbols by differential encoding on a transmitting side, and to make identification and decision of the data by differential detection on a receiving side.

In the differential detection, however, one bit error in a radio section causes two bit error because the data to be transmitted is modulated with the differential encoding as mentioned above. Thus, 5 under the same SNIR (Signal to Noise and Interference power Ratio), the received error rate will increase by 3 dB from that of the coherent detection such as binary phase shift keying (BPSK).

On the other hand, although the coherent 10 detection that decides the phase of a received signal for each data symbol by the absolute phase has highly efficient receiving characteristics, it is difficult to decide the received absolute phase in a Rayleigh fading environment.

15 To solve the problem, a method is proposed that insert pilot symbols into a data symbol sequence, and carries out channel estimation of the data symbols using the pilot symbols. As a pilot symbol insertion method, there are a time multiplexed pilot 20 channel method that inserts pilot symbols between data symbols, and a parallel pilot channel method that inserts pilot symbols in parallel with data symbols.

The following references 1-3 propose a channel 25 estimation method based on the time multiplexed pilot channel method.

Reference 1: Seiichi Sampei and Terumi Sunaga,
"Rayleigh Fading Compensation for QAM in Land Mobile
Radio Communication", IEEE Trans. Vehicular Technol.
VT-42, No.2, May 1993. It proposes a method of
5 estimating and compensating for the fading
distortion using pilot symbols that are inserted
between data symbols at fixed intervals and have
known phases. In this method, a pilot symbol is
inserted at every several data symbol intervals, and
10 the channel estimation is carried out based on the
received phases of the pilot symbols. In other
words, it measures the amplitude and phase of the
received signal of each path of each user at the
pilot symbols before and after the current data
15 symbol section, and estimates the channel
fluctuations in the data symbol section by
interpolating the measured values.

Reference 2: Hidehiro Ando et.al, "Channel
Estimation Filter Using Time-Multiplexed Pilot
20 Channel for Coherent RAKE Combining in DS-CDMA",
Mobile Radio, IEICE Trans. Commun. Vol.81-B, No.7,
July 1998. It proposes a method of carrying out
more highly accurate channel estimation by making
channel estimation using more pilot symbols.

25 Fig. 23 is a diagram illustrating a channel
estimation method based on the reference 2. In this

method, the transmission power control is carried out at every slot interval to follow instantaneous Rayleigh fluctuations. Therefore, as illustrated in Fig. 23, the amplitude (power) of the combined
5 symbol sequence of data symbols and pilot symbols varies at every slot interval, and the phase also varies slightly due to the operation of an amplifier during transmission. Such transmission power control enables a reverse channel of the DS-CDMA
10 (Direct Sequence CDMA) to secure the SNIR against interference signals caused by cross-correlation with other users.

The channel estimation of the data symbols is performed using pilot symbols inserted between data
15 symbols at fixed intervals. Specifically, it is carried out by averaging (taking coherent sums of) pilot symbols (estimated complex fading envelopes) in a plurality of slots before and after the slot, to which the data symbols to be subjected to the
20 channel estimation belong, and by obtaining a channel estimation value $\tilde{\xi}$ by taking the weighted sum (weighted average) of the average values $\bar{\xi}$ using weighting factors α_0, α_1 and so on, thereby achieving highly accurate channel estimation.

Using many pilot symbols belonging to different slots enables highly accurate channel estimation. This is because in an actual mobile propagation environment, interference signals, which are
5 generated by thermal noise (to minimize the transmission power, a noise limited environment is created particularly at cell edges), and by cross-correlation from other users, are added to the desired signal of the current channel, and the
10 channel estimation accuracy is degraded because of the phase and amplitude of the received signal that vary at every moment due to fading. Although the pilot symbols in different slots have different power, the channel estimation error due to the power
15 difference is less than the reduction effect by the thermal noise and interference signals caused from using pilot symbols in more slots.

The reference 2 method assumes that the channel fluctuations in each slot are small, and employs the
20 same weighting factors α for all the data symbols in each slot to obtain the same channel estimation value $\tilde{\xi}$. This presents a problem of impairing the characteristics in high rate fading.

Reference 3, Sadayuki Abeta et.al, "Performance
25 Comparison between Time-Multiplexed Pilot Channel

and Parallel Pilot Channel for Coherent Rake
Combining in DS-CDMA Mobile Radio", IEICE Trans.
Commun. Vol.81-B, No.7, July 1998. It proposes a
method of achieving highly accurate channel

5 estimation in making channel estimation of the data
symbols by obtaining a channel estimation value by
appropriately taking weighted sum of the pilot
symbols in a plurality of slots before and after the
slot, to which the current data symbols belong,
10 using appropriate weighting factors for each data
symbol in the same slot (weighting factors $\alpha_{m,0}$, $\alpha_{m,1}$
and so on for m-th data symbol in the slot). First
to fourth embodiments in accordance with the present
invention apply this scheme (see, Fig. 3).

15 For example, in Fig. 23, for the (m-A)-th data
symbol in the n-th slot, where A is a natural
number, the pilot symbols in the n-th slot are
assigned a greatest weight. This is because the
pilot symbols in the n-th slot are closest (in time)
20 to the (m-A)-th data symbol, and hence best reflect
the channel state when receiving the data symbols.
In contrast, for the (m+B)-th data symbol in the n-
th slot, where B is a natural number, the pilot
symbols in the (n+1)-th slot are assigned a greatest
25 weight. This is because the pilot symbols in the
(n+1)-th slot are closest (in time) to the (m+B)-th

data symbol, and hence best reflect the channel state when receiving the data symbols.

As for the parallel pilot channel method, the following reference 4 and the foregoing reference 3
5 disclose a channel estimation method based on the method.

Reference 4, Sadayuki Abeta et.al, "DS/CDMA Coherent Detection System with a Suppressed Pilot Channel", IEEE GLOBECOM'94, pp. 1622-1626, 1994. It
10 proposes a method of estimating and compensating for the fading distortion by inserting pilot channel having known phase in parallel with and perpendicular to the data channel for transmitting data.

15 The channel estimation of the data symbols is carried out by averaging the pilot symbols in a section to which the target data symbol belongs, and by obtaining the channel estimation value. Thus, the channel estimation with high SNIR is achieved.
20 By using the estimation value, the received signal in each path of each user is detected at the positions of the pilot symbols in the current data symbol section, and the amplitude and phase measurement is carried out for the signal of each
25 path so as to estimate and compensate for the channel fluctuations in the data symbol section.

When performing the channel estimation of the data symbols in the reference 4 method, the average of the pilot symbols is calculated only within the slot including the target data symbol, and the
5 average is made the channel estimation value.

The foregoing reference 3 proposes a method of achieving more highly accurate channel estimation by obtaining a more highly accurate channel estimation value by taking weighted sum of the pilot symbols
10 appropriately when carrying out the channel estimation of the data symbols. This method is applied to the fifth to eighth embodiments in accordance with the present invention (see, Fig. 14).

15 Fig. 14 illustrates the channel estimation method disclosed by the reference 3. In Fig. 14, the channel estimation is carried out using a pilot symbol sequence parallel to the data symbol sequence. Specifically, it obtains the channel
20 estimation value $\tilde{\xi}$ by generating a plurality of pilot blocks from the pilot symbols, by averaging the pilot symbols in each of the pilot blocks, and by taking a weighted sum of the average values $\bar{\xi}$ using weighting factors α_1, α_{-1} and so on, thereby
25 achieving highly accurate channel estimation. Using

many pilot symbols belonging to different slots in carrying out the channel estimation enables the highly accurate channel estimation.

To suppress the power loss, the power of the pilot symbol sequence is set less than that of the data symbol sequence. In addition, to follow the instantaneous Rayleigh fluctuations, the transmission power control is performed at every slot interval. This enables the reverse channel in the DS-CDMA to secure the SNIR against the interference signals caused by the cross-correlation from other users.

The methods disclosed in the foregoing references 3 and 4, however, use constant weighting values regardless of the fading fluctuations. This presents a problem in that when setting optimum weighting values for low rate fading fluctuations, the highly accurate channel estimation cannot be achieved in the high rate fading, whereas when setting optimum weighting values for high rate fading fluctuations, the highly accurate channel estimation cannot be achieved in the low rate fading.

DISCLOSURE OF THE INVENTION

The present invention is implemented to solve the foregoing problems. It is therefore an object of the present invention to improve the resistance to fading fluctuations and to carry out the highly accurate channel estimation by adaptively optimizing the weighting values for the pilot symbols in response to the rate of channel fluctuations.

Achieving highly accurate channel estimation and compensation of channel fluctuations of data symbols based on the channel estimation makes it possible to decide the absolute phase of each data symbol under a Rayleigh fading environment using the coherent detection, and to reduce the SNIR required for obtaining a predetermined level of receiving quality (receiving error rate). Therefore, the transmission power can be reduced, and the capacity in terms of the number of users of the system can be increased.

In order to accomplish the object aforementioned, according to the invention as claimed in claim 1, a CDMA receiver for receiving and demodulating a signal including a combined symbol sequence that has a plurality of slots and includes data symbols and pilot symbols, comprises:

- means for detecting positions of the pilot symbols in the combined symbol sequence;

means for generating pilot blocks by extracting in a plurality of slots the pilot symbols from the combined symbol sequence in response to a result of the detection;

5 means for obtaining channel estimation values by calculating a weighted sum of average values of the pilot symbols in the pilot blocks;

means for acquiring from the combined symbol sequence a data symbol sequence in accordance with
10 the result of the detection;

means for compensating for channel fluctuations of the data symbol sequence using the channel estimation values; and

means for controlling the weighting in response
15 to a rate of the channel fluctuations.

According to the invention as claimed in claim 2, in the CDMA receiver as claimed in claim 1, the means for controlling the weighting comprises:

means for compensating for, using the channel
20 estimation values, channel fluctuations of a pilot symbol sequence extracted from the combined symbol sequence;

means for generating an error signal from the compensated pilot symbol sequence and an ideal pilot
25 symbol sequence; and

means for carrying out the weighting control using the error signal and the average values of the pilot symbols included in the pilot blocks.

According to the invention as claimed in claim
5 3, in the CDMA receiver as claimed in claim 1, the means for controlling the weighting comprises:

means for generating an error signal from the compensated data symbol sequence and from result obtained by demodulating and deciding the
10 compensated data symbol sequence; and

means for carrying out the weighting control using the error signal and the average values of the pilot symbols included in the pilot blocks.

According to the invention as claimed in claim
15 4, in the CDMA receiver as claimed in claim 1, the means for controlling the weighting carries out the weighting control using as update values inner products of the channel estimation values of the data symbols and the average values of the pilot
20 symbols included in the pilot blocks.

According to the invention as claimed in claim
5, in the CDMA receiver as claimed in any one of claims 1-4, the CDMA receiver receives a signal including a combined symbol sequence having a frame
25 structure consisting of slots in which the pilot symbols consisting of a few symbols are inserted

into the data symbol sequence at every fixed interval.

According to the invention as claimed in claim 6, in the CDMA receiver as claimed in any one of
5 claims 1-5, the pilot blocks are formed from all the pilot symbols in a slot.

According to the invention as claimed in claim 7, in the CDMA receiver as claimed in any one of claims 1-6, when obtaining the channel estimation
10 value of a data symbol in an n -th slot of the combined symbol sequence, where n is an integer, the pilot blocks are generated from an $(n-K+1)$ -th slot to an $(n+K)$ -th slot of the combined symbol sequence, where K is a natural number.

15 According to the invention as claimed in claim 8, a CDMA receiver for receiving and demodulating a signal including a data symbol sequence and a pilot symbol sequence parallel to the data symbol sequence, comprises:

20 means for generating a plurality of pilot blocks from the pilot symbol sequence;

means for obtaining channel estimation values by calculating a weighted sum of average values of the pilot symbols in the pilot blocks;

means for compensating for channel fluctuations of the data symbol sequence using the channel estimation values; and

5 means for controlling the weighting in response to a rate of the channel fluctuations.

According to the invention as claimed in claim 9, in the CDMA receiver as claimed in claim 8, the means for controlling the weighting comprises:

10 means for compensating for, using the channel estimation values, channel fluctuations of the pilot symbol sequence;

means for generating an error signal from the compensated pilot symbol sequence and an ideal pilot symbol sequence; and

15 means for carrying out the weighting control using the error signal and the average values of the pilot symbols included in the pilot blocks.

According to the invention as claimed in claim 10, in the CDMA receiver as claimed in claim 8, the
20 means for controlling the weighting comprises:

means for generating an error signal from the compensated data symbol sequence and from result obtained by demodulating and deciding the compensated data symbol sequence; and

means for carrying out the weighting control using the error signal and the average values of the pilot symbols included in the pilot blocks.

According to the invention as claimed in claim 5 11, in the CDMA receiver as claimed in claim 8, the means for controlling the weighting carries out the weighting control using as update values inner products of the channel estimation values of the data symbols and the average values of the pilot 10 symbols included in the pilot blocks.

According to the invention as claimed in claim 12, in the CDMA receiver as claimed in any one of claims 8-11, the CDMA receiver receives a signal including a data symbol sequence which is spread 15 using a first spreading code, and a pilot symbol sequence which is parallel to the data symbol sequence and spread using a second spreading code, the first spreading code and the second spreading code being orthogonal to each other.

20 According to the invention as claimed in claim 13, in the CDMA receiver as claimed in any one of claims 8-12, the CDMA receiver receives a signal including a spread data symbol sequence which is impressed on a first carrier, and a spread pilot 25 symbol sequence which is parallel to the data symbol sequence and is impressed on a second carrier, the

first carrier and the second carrier being orthogonal to each other.

According to the invention as claimed in claim 14, in the CDMA receiver as claimed in any one of
5 claims 8-13, when obtaining the channel estimation value of an n -th data symbol in the data symbol sequence, where n is an integer, the plurality of pilot blocks are generated from an $(n-K+1)$ -th pilot symbol to an $(n+K)$ -th pilot symbol in the pilot
10 symbol sequence, where K is a natural number.

According to the invention as claimed in claim 15, in the CDMA receiver as claimed in any one of claims 8-14, the plurality of pilot blocks have a same length.

15 According to the invention as claimed in claim 16, a CDMA transceiver includes a transmitting section for transmitting a signal including a combined symbol sequence that has a plurality of slots and includes data symbols and pilot symbols,
20 and a receiving section for receiving and demodulating the signal, and the receiving section comprises:

means for detecting positions of the pilot symbols in the combined symbol sequence;

25 means for generating pilot blocks by extracting, in a plurality of slots, the pilot symbols from the

combined symbol sequence in response to a result of the detection;

means for obtaining channel estimation values by calculating a weighted sum of average values of the pilot symbols included in the pilot blocks;

means for acquiring from the combined symbol sequence a data symbol sequence in accordance with the result of the detection;

means for compensating for channel fluctuations of the data symbol sequence using the channel estimation values; and

means for controlling the weighting in response to a rate of the channel fluctuations.

According to the invention as claimed in claim 17, a CDMA transceiver includes a transmitting section for transmitting a signal including a data symbol sequence and a pilot symbol sequence parallel to the data symbol sequence, and a receiving section for receiving and demodulating the signal, and the receiving section comprises:

means for generating a plurality of pilot blocks from the pilot symbol sequence;

means for obtaining channel estimation values by calculating a weighted sum of average values of the pilot symbols in the pilot blocks;

means for compensating for channel fluctuations of the data symbol sequence using the channel estimation values; and

means for controlling the weighting in response
5 to a rate of the channel fluctuations.

According to the invention as claimed in claim 18, a CDMA receiving method of receiving and demodulating a signal including a combined symbol sequence that has a plurality of slots and includes
10 data symbols and pilot symbols, comprises the steps of:

detecting positions of the pilot symbols in the combined symbol sequence;

generating pilot blocks by extracting, in a
15 plurality of slots, the pilot symbols from the combined symbol sequence in response to a result of the detection;

obtaining channel estimation values by
calculating a weighted sum of average values of the
20 pilot symbols in the pilot blocks;

acquiring from the combined symbol sequence a data symbol sequence in accordance with the result of the detection; and

compensating for channel fluctuations of the
25 data symbol sequence using the channel estimation value,

wherein the weighting is controlled in response to a rate of the channel fluctuations.

According to the invention as claimed in claim 19, a CDMA receiving method of receiving and
5 demodulating a signal including a data symbol sequence and a pilot symbol sequence parallel to the data symbol sequence, comprises the steps of:

generating a plurality of pilot blocks from the pilot symbol sequence;
10 obtaining channel estimation values by calculating a weighted sum of average values of the pilot symbols in the pilot blocks; and
compensating for channel fluctuations of the data symbol sequence using the channel estimation
15 value,
wherein the weighting is controlled in response to a rate of the channel fluctuations.

BRIEF DESCRIPTION OF THE DRAWINGS

20 Fig. 1 is a block diagram showing a configuration of a CDMA receiver of a first embodiment in accordance with the present invention;

Fig. 2 is a diagram showing relationship between Figs. 2A and 2B;

Fig. 2A is a flowchart illustrating a receiving processing by the CDMA receiver of the first embodiment in accordance with the present invention;

Fig. 2B is a flowchart illustrating the
5 receiving processing by the CDMA receiver of the first embodiment in accordance with the present invention;

Fig. 3 is a diagram illustrating the operation principle of the channel estimation by the CDMA
10 receiver of the first embodiment in accordance with the present invention, taking an example of the channel estimation;

Fig. 4 is a flowchart illustrating a weighting control processing by the CDMA receiver of the first
15 embodiment in accordance with the present invention;

Fig. 5 is a block diagram showing a configuration of a CDMA transceiver of a second embodiment in accordance with the present invention;

Fig. 6 is a block diagram showing a
20 configuration of a transmission processor of the CDMA transceiver in the second embodiment in accordance with the present invention;

Fig. 7 is a flowchart illustrating a transmission processing by the transmission
25 processor of the CDMA transceiver in the second embodiment in accordance with the present invention;

Fig. 8 is a block diagram showing a configuration of the CDMA receiver of a third embodiment in accordance with the present invention;

Fig. 9 is a flowchart illustrating a weighting
5 control processing by the CDMA receiver of the third embodiment in accordance with the present invention;

Fig. 10 is a block diagram showing a configuration of the CDMA receiver of a fourth embodiment in accordance with the present invention;

10 Fig. 11 is a flowchart illustrating a weighting control processing by the CDMA receiver of the fourth embodiment in accordance with the present invention;

Fig. 12 is a block diagram showing a
15 configuration of the CDMA receiver of a fifth embodiment in accordance with the present invention;

Fig. 13 is a diagram showing relationship between Figs. 13A and 13B;

Fig. 13A is a flowchart illustrating a receiving
20 processing by the CDMA receiver of the fifth embodiment in accordance with the present invention;

Fig. 13B is a flowchart illustrating the receiving processing by the CDMA receiver of the fifth embodiment in accordance with the present
25 invention;

Fig. 14 is a diagram illustrating the operation principle of the channel estimation by the CDMA receiver of the fifth embodiment in accordance with the present invention, taking an example of channel
5 estimation;

Fig. 15 is a block diagram showing a configuration of a CDMA transceiver of a sixth embodiment in accordance with the present invention;

Fig. 16 is a block diagram showing a
10 configuration of a transmission processor of the CDMA transceiver in the sixth embodiment in accordance with the present invention;

Fig. 17 is a flowchart illustrating a
15 transmission processing by the transmission processor of the CDMA transceiver in the sixth embodiment in accordance with the present invention;

Fig. 18 is a block diagram showing a configuration of the CDMA receiver of a seventh embodiment in accordance with the present invention;

20 Fig. 19 is a block diagram showing a configuration of the CDMA receiver of an eighth embodiment in accordance with the present invention;

Fig. 20 is a diagram illustrating required error rate ($BER=10^{-3}$) characteristics for the product of a
25 slot time (T_{slot}) and a maximum Doppler frequency (f_d) under a two-path Rayleigh model;

Fig. 21 is a diagram illustrating BER characteristics under a Vehicular-B environment when $f_d T_{slot} = 0.003125$ and $f_d T_{slot} = 0.28$;

Fig. 22 is a diagram showing required error rate (BER= 10^{-3}) characteristics for $f_d T_{slot}$ under a Vehicular-B environment; and

Fig. 23 is a diagram illustrating the operation principle of channel estimation in accordance with a related art.

10

BEST MODE FOR CARRYING OUT THE INVENTION

The best mode for carrying out the invention will now be described with reference to the accompanying drawings.

15

First to fourth embodiments in accordance with the present invention relates to a CDMA receiver or a CDMA transceiver based on the time multiplexed pilot channel method, and fifth to eighth embodiments in accordance with the present invention relates to a CDMA receiver or a CDMA transceiver based on the parallel pilot channel method.

20

[FIRST EMBODIMENT]

Fig. 1 is a block diagram showing a configuration of a CDMA receiver of a first embodiment in accordance with the present invention. The CDMA receiver 100 of the present embodiment

25

receives and demodulates a signal including a combined symbol sequence that has a plurality of slots and includes data symbols and pilot symbols.

The CDMA receiver 100 comprises a receiving
5 section 110, a matched filter 125, a slot
synchronization detector 101, a pilot symbol
sequence acquisition section 112, a pilot block
generator 111, a channel estimation value
acquisition section 121, a data symbol sequence
10 acquisition section 129, a data symbol sequence
compensator 130, a RAKE combiner 132, an error
signal generator 142, and a weighting controller
(MMSE) 144. Although in the present embodiment, the
matched filter 125, slot synchronization detector
15 101 and the like are implemented by software using a
DSP (Digital Signal Processor) (plus a memory for
storing programs) 120 as shown in Fig. 1, they can
be implemented by means of hardware, in which case
delay circuits and other components are used as
20 needed.

Figs. 2A and 2B are a flowchart illustrating a
receiving processing by the CDMA receiver of the
present embodiment. First, at step S201, the
receiving section 110 receives a receiving signal,
25 that is, a spread combined symbol sequence. At step
S202, the matched filter 125 despreads the received

signal to generate a combined symbol sequence.

Subsequently, at steps S203-S208, the slot synchronization detector 101, pilot symbol sequence acquisition section 112, pilot block generator 111 and channel estimation value acquisition section 121 carry out the channel estimation processing, thereby acquiring channel estimation values of the data symbols and pilot symbols.

Fig. 3 is a diagram illustrating the operation principle of the channel estimation by a channel estimation unit of the present embodiment by way of example of acquiring channel estimation values of an m -th data symbol in n -th slot, where n and m are integers. The combined symbol sequence in the example as shown in Fig. 3 is subjected to the transmission power control at every slot interval. Each slot of the combined symbol sequence has a form in which a fixed length pilot symbols are followed by a fixed length data symbols. In other words, the combined symbol sequence has a frame structure in which a unit of a few pilot symbols is inserted into the data symbol sequence at every fixed interval.

Alternatively, the length of the data symbols and/or pilot symbols in each slot of the combined symbol sequence may be one symbol length, or made variable. Besides, there may be a slot consisting

of only the data symbols or pilot symbols. In addition, the arrangement of the data symbols and pilot symbols in each slot can be free.

Returning to Fig. 2A, the slot synchronization
5 detector 101 detects the position of the pilot symbols in the combined symbol sequence at step S203.

Subsequently, at step S204, the pilot symbol
sequence acquisition section 112 and pilot block
10 generator 111 extract the pilot symbols from a plurality of slots in the combined symbol sequence, and generates pilot blocks. Specifically, the pilot symbol sequence acquisition section 112 acquires the pilot symbols (sequence) from the plurality of slots
15 on the basis of the detection result at step S203, and the pilot block generator 111 generates pilot blocks from the pilot symbols acquired.

In the example as shown in Fig. 3, the pilot symbols are extracted from the combined symbol
20 sequence over a range from the $(n-K+1)$ -th slot to the $(n+K)$ -th slot, where K is a natural number and is set at three in Fig. 3, to generate pilot blocks. A pilot block is a set of the pilot symbols.

Although each pilot block is formed from all the
25 pilot symbols in a slot in the present embodiment, it can be formed from part of the pilot symbols in

the slot. It is also possible to form one pilot block from one pilot symbol. Besides, the number of pilot symbols in a pilot block can be made variable from slot to slot.

5 When obtaining the channel estimation values of the data symbols in the n-th slot, it is not essential to form the pilot blocks from nearly the same numbers of the slots before and after the n-th slots as in the example of Fig. 3. For example, the
10 pilot blocks can be generated only from the slots with the number smaller than (previous to) the n-th slot, considering the delay of the channel estimation.

Through steps S205-S208, the channel estimation
15 value acquisition section 121 acquires the channel estimation values of the data symbols and pilot symbols. First, at step S205, it averages the pilot symbols $\hat{\xi}$ (estimated complex fading envelopes) contained in each pilot block, thereby obtaining a
20 pilot block average value $\bar{\hat{\xi}}$. This step is carried out for all the pilot blocks (step S206). When a pilot block consists of only one pilot symbol, the pilot symbol $\hat{\xi}$ itself is adopted as the pilot block average value $\bar{\hat{\xi}}$. In the example as shown in Fig. 3,
25 pilot block average values $\bar{\hat{\xi}}(n+i)$ are obtained for

the pilot blocks in the (n+i)-th slots, where i varies from -K+1 to K (K=3).

At step S207, the channel estimation values $\tilde{\xi}_m$ of the data symbols and pilot symbols are obtained by taking a weighted sum of the pilot block average values $\bar{\xi}$ weighted by the weighting factors α , respectively. In the example of Fig. 3, the channel estimation value $\tilde{\xi}_m(n)$ is obtained for the m-th data symbol in the n-th slot with placing the weighting factors of the (n+i)-th pilot blocks at $\alpha_{m,i}$.

In the present embodiment, the channel estimation values are also obtained for the pilot symbols to carry out the weighting control. The channel estimation values are obtained in the same manner as those of the data symbols. Specifically, the channel estimation value $\tilde{\xi}_m(n)$ is obtained for the m-th pilot symbol in the n-th slot with placing the weighting factors of the (n+i)-th pilot block at $\alpha_{m,i}$.

The channel estimation value $\tilde{\xi}_m(n)$ is given by the following equation (1).

$$\tilde{\xi}_m(n) = \sum_{i=-K+1}^K \alpha_{m,i} \cdot \bar{\xi}(n+i) \quad (1)$$

The foregoing step S207 is repeated for all the data symbols and pilot symbols for which the channel estimation values are to be obtained (step S208).

It is also possible to use the same weighting
5 factors for all the data symbols and pilot symbols in one slot to obtain the channel estimation values.

At step S209 after obtaining the channel estimation values, the data symbol sequence acquisition section 129 obtains the data symbol
10 sequence from the combined symbol sequence on the basis of the detection result of the slot synchronization detector 101.

At step S210, the data symbol sequence compensator 130 compensates for the channel
15 fluctuations (fading phase fluctuations) of the data symbol sequence using the channel estimation values $\tilde{\xi}_m$ (of the data symbols) obtained through steps S203-S208. More specifically, it compensates for the channel fluctuations of the data symbols by
20 multiplying the data symbol sequence by the complex conjugates of the channel estimation values $\tilde{\xi}_m$.

At step S211, the RAKE combiner 132 carries out coherent combining of the compensated data symbol sequences fed from respective RAKE fingers.

Fig. 4 is a flowchart illustrating a weighting control processing by the CDMA receiver of the present embodiment. At step S401, the pilot symbol sequence compensator 146 compensates for the channel fluctuations of the pilot symbol sequence using the channel estimation values $\tilde{\xi}_m$ (of the pilot symbols) obtained through steps S203-S208.

At step S402, the error signal generator 142 generates an error signal (identification error information) from the compensated pilot symbol sequence and ideal pilot symbol sequence (which is free from the channel fluctuations). The ideal pilot symbol sequence is known, and is prepared in advance in the receiver 100.

At step S403, the weighting controller (MMSE) 144 controls the weighting (weighting factors $\alpha_{m,i}$), using the error signal and the pilot block average values (the channel estimation values obtained from individual pilot blocks) $\bar{\xi}$ as feedback information.

Thus adaptively optimizing the weighting values for the pilot symbols in response to the channel fluctuation rate makes it possible to improve the resistance to fading fluctuations, and to carry out the highly accurate channel estimation.

25

[SECOND EMBODIMENT]

Fig. 5 is a block diagram showing a configuration of a CDMA transceiver of a second embodiment in accordance with the present invention.

5 The CDMA transceiver 500 of the present embodiment transmits a signal including a combined symbol sequence that has a plurality of slots and includes data symbols and pilot symbols, and receives and demodulates such a signal.

10 The CDMA transceiver 500 comprises a transmitting processor 510 and a receiving processor 520. The configuration, receiving processing and weighting control processing of the receiving processor 520 are the same as the configuration
15 (Fig. 1), receiving processing (Figs. 2A and 2B) and weighting control processing (Fig. 4) of the CDMA receiver 100 of the first embodiment in accordance with the present invention.

Fig. 6 is a block diagram showing a
20 configuration of the transmitting processor of the CDMA transceiver in the second embodiment. As shown in Fig. 6, the transmitting processor 510 comprises a transmitting section 610, a channel encoder 622, a combiner 630 and a spreader 627. Although in the
25 present embodiment, the channel encoder 622, combiner 630 and the like are implemented by

software using a DSP (plus a memory for storing programs) 620 as shown in Fig. 6, they can be implemented by means of hardware.

Fig. 7 is a flowchart illustrating a transmission processing by the transmitting processor of the CDMA transceiver in the present embodiment. First, at step S701, the channel encoder 622 modulates (encodes) a data sequence, thereby generating a data symbol sequence. At step S702, the combiner 630 inserts pilot symbols into each slot of the data symbol sequence, thereby generating a combined symbol sequence. At step S703, the spreader 627 spreads the combined symbol sequence, thereby generating a transmitted signal (spread combined symbol sequence). At step S704, the transmitting section 610 transmits the transmitted signal.

[THIRD EMBODIMENT]

Fig. 8 is a block diagram showing a CDMA receiver of a third embodiment in accordance with the present invention. The CDMA receiver 800 of the present embodiment receives a signal including a combined symbol sequence that has a plurality of slots and contains data symbols and pilot symbols.

The CDMA receiver 800 comprises a receiving section 810, a matched filter 825, a slot synchronization detector 801, a pilot symbol sequence acquisition section 812, a pilot block generator 811, a channel estimation value acquisition section 821, a data symbol sequence acquisition section 829, a data symbol sequence compensator 830, a RAKE combiner 832, a data decision section 846, an error signal generator 842, and a weighting controller (MMSE) 844. Although in the present embodiment, the matched filter 825, slot synchronization detector 801 and the like are implemented by software using a DSP (plus a memory for storing programs) 820 as shown in Fig. 8, they can be implemented by means of hardware. The configurations and functions of the receiving section 810, matched filter 825 and the like are the same as those of their counterparts in the CDMA receiver 100 in the first embodiment in accordance with the present invention. In addition, the CDMA receiver 800 of the present embodiment carries out the same processing as the receiving processing (Figs. 2A and 2B) of the CDMA receiver 100 in the first embodiment in accordance with the present invention, except that it is unnecessary to obtain

the channel estimation values of the pilot symbols in the present embodiment.

Fig. 9 is a flowchart illustrating a weighting control processing by the CDMA receiver of the present embodiment. At step S901, the error signal generator 842 generates an error signal (identification error information) from the compensated data symbol sequence and from result obtained by demodulating and deciding the compensated data symbol sequence. The data decision is carried out by the data decision section 846 that makes a decision (0/1) of the output of the RAKE combiner 832.

At step S902, the weighting controller (MMSE) 844 carries out the control of weighting (weighting factors $\alpha_{m,i}$) using the error signal and the pilot block average values (the channel estimation values obtained from the individual pilot blocks) $\hat{\xi}$ as the feedback information.

Thus adaptively optimizing the weighting values for the pilot symbols in response to the channel fluctuation rate makes it possible to improve the resistance to fading fluctuations, and to carry out the highly accurate channel estimation.

Furthermore, since the weighting factors can be updated not at the pilot symbol intervals (slot intervals) but at the symbol intervals in the present embodiment, the convergence capability of
5 the weighting factors can be improved.

Incidentally, a CDMA transceiver can be arranged by employing the CDMA receiver 800 of the third embodiment in accordance with the present invention as the receiving processor, and the transmitting
10 processor 510 of the CDMA transceiver 500 of the second embodiment in accordance with the present invention as the transmitting processor.

[FOURTH EMBODIMENT]

15 Fig. 10 is a block diagram showing a CDMA receiver of a fourth embodiment in accordance with the present invention. The CDMA receiver 1000 of the present embodiment receives and demodulates a signal including a combined symbol sequence that has
20 a plurality of slots and includes both data symbols and pilot symbols.

The CDMA receiver 1000 comprises a receiving section 1010, a matched filter 1025, a slot synchronization detector 1001, a pilot symbol
25 sequence acquisition section 1012, a pilot block generator 1011, a channel estimation value

acquisition section 1021, a data symbol sequence
acquisition section 1029, a data symbol sequence
compensator 1030, a RAKE combiner 1032, and a
weighting controller (inner product calculator)
5 1044. Although in the present embodiment, the
matched filter 1025, slot synchronization detector
1001 and the like are implemented by software using
a DSP (plus a memory for storing programs) 1020 as
shown in Fig. 10, they can be implemented by means
10 of hardware. The configurations and functions of
the receiving section 1010, matched filter 1025 and
the like are the same as those of their counterparts
of the CDMA receiver 100 of the first embodiment in
accordance with the present invention. Besides, the
15 CDMA receiver 1000 of the present embodiment carries
out the same processing as the receiving processing
(Figs. 2A and 2B) of the CDMA receiver 100 of the
first embodiment in accordance with the present
invention, except that it is unnecessary for the
20 CDMA receiver 1000 of the present embodiment to
obtain the channel estimation values of the pilot
symbols.

Fig. 11 is a flowchart illustrating a weighting
control processing by the CDMA receiver of present
25 embodiment. At step S1101, the weighting controller
(inner calculation) 1044 carries out the control

(updating) of the weighting (weighting factors $\alpha_{m,i}$) as the following equation (2), using the inner products (correlation values) of the channel estimation values $\tilde{\xi}$ of the data symbols and the pilot block average values (channel estimation values obtained from the individual pilot blocks) $\bar{\xi}$ as the update values (feedback information).

$$\left. \begin{aligned} \mathbf{A}_m(n) &= \mathbf{A}_m(n-1) + \mu \tilde{\xi}_m(n) \bar{\mathbf{X}}(n) \\ \mathbf{A}_m(n) &= \begin{pmatrix} \alpha_{m,-K+1}(n) \\ \alpha_{m,-K+2}(n) \\ \vdots \\ \alpha_{m,K-1}(n) \\ \alpha_{m,K}(n) \end{pmatrix}, \bar{\mathbf{X}}(n) = \begin{pmatrix} \bar{\xi}(n-K+1) \\ \bar{\xi}(n-K+2) \\ \vdots \\ \bar{\xi}(n+K-1) \\ \bar{\xi}(n+K) \end{pmatrix} \\ \tilde{\xi}_m(n) &= \mathbf{A}_m^t(n-1) \cdot \bar{\mathbf{X}}(n) \end{aligned} \right\} (2)$$

10

where, $\mathbf{A}_m(n)$ is the weighting factor of the m-th data symbol in the n-th slot, μ is a step size of the updating, $\bar{\xi}(n+i)$ is the pilot block average value of the (n+i)-th slot, and $\tilde{\xi}_m(n)$ is the channel estimation value of the m-th data symbol in the n-th

15

slot. In addition, $A_m^t(n)$ denotes the transpose of $A_m(n)$.

Thus adaptively optimizing the weighting values for the pilot symbols in response to the channel fluctuation rate makes it possible to improve the resistance to fading fluctuations, and to carry out the highly accurate channel estimation.

Furthermore, it is unnecessary for the present embodiment to demodulate the data or to generate the error signal, which makes it possible to carry out the weighting control in response to the channel fluctuations with a simple configuration.

Incidentally, a CDMA transceiver can be configured by employing the CDMA receiver 1000 of the fourth embodiment in accordance with the present invention as the receiving processor, and the transmitting processor 510 of the CDMA transceiver 500 of the second embodiment in accordance with the present invention as the transmitting processor.

20

[FIFTH EMBODIMENT]

Fig. 12 is a block diagram showing a configuration of the CDMA receiver of the fifth embodiment in accordance with the present invention. The CDMA receiver 1200 of the present embodiment

25

receives and demodulates a signal including a data symbol sequence and a pilot symbol sequence parallel to the data symbol sequence.

The CDMA receiver 1200 comprises a receiving
5 section 1210, a data symbol sequence matched filter 1224, a pilot symbol sequence matched filter 1226, a pilot block generator 1211, a channel estimation value acquisition section 1221, a data symbol sequence compensator 1230, a RAKE combiner 1232, an
10 error signal generator 1242, and a weighting controller (MMSE) 1244.

Although in the present embodiment, the data symbol sequence matched filter 1224, pilot symbol sequence matched filter 1226 and the like are
15 implemented by software using a DSP (plus a memory for storing programs) 1220 as shown in Fig. 12, they can also be implemented by means of hardware.

Figs. 13A and 13B are flowcharts illustrating a receiving processing by the CDMA receiver of the
20 present embodiment. First, at step S1301, the receiving section 1210 receives a received signal, that is, a spread data symbol sequence and a spread pilot symbol sequence.

In the present embodiment, it is assumed that
25 the data symbol sequence and the pilot symbol sequence are spread by a first spreading code and a

second spreading code, respectively, which are orthogonal to each other. However, it is also possible to receive such data symbol sequence and pilot symbol sequence that are spread by a first
5 spreading code and a second spreading code that are not orthogonal to each other.

In addition, it is assumed in the present embodiment that the spread data symbol sequence and the spread pilot symbol sequence are impressed
10 (transmitted) on a first carrier and a second carrier, respectively, which are orthogonal to each other. However, it is also possible to receive such data symbol sequence and pilot symbol sequence that are impressed on a first carrier and a second
15 carrier that are not orthogonal to each other. As a typical example of the carriers that are orthogonal to each other, there are sine waves and cosine waves.

At step S1302, the data symbol sequence matched
20 filter 1224 generates the data symbol sequence by despreading the received signal using the first spreading code. At step S1303, the pilot symbol sequence matched filter 1226 generates the pilot symbol sequence by despreading the received signal
25 using the second spreading code. Subsequently, through steps S1304-S1308, the pilot block generator

1211 and channel estimation value acquisition section 1221 carry out the channel estimation, thereby obtaining the channel estimation values of the data symbols and pilot symbols.

5 Fig. 14 is a diagram illustrating the operation principle of the channel estimation by the channel estimation unit of the present embodiment, taking an example of obtaining the channel estimation value of the n-th data symbol, where n is an integer. In the
10 example as shown in Fig. 14, the power of the pilot symbol sequence is made less than that of the data symbol sequence to suppress the power loss. In addition, the data symbol sequence and pilot symbol sequence are subjected to the transmission power
15 control at every slot interval.

Returning to Fig. 13A, the pilot block generator 1211 generates a plurality of pilot blocks from the pilot symbol sequence at step S1304. In the example as shown in Fig. 14, to generates L (three, in this
20 example) pilot blocks of λ bits before and after the n-th pilot symbol, pilot symbols from (n-K+1)-th to (n+K)-th pilot symbol are used, where K is a natural number equal to $L \times \lambda$.

It is preferable that the pilot blocks be formed
25 from pilot symbols belonging to many different slots to use these pilot symbols for the channel

estimation. This is because although the pilot symbols belonging to different slots have different power, the effect of reduction in thermal noise and interfering signals by using pilot symbols in more slots is greater than the channel estimation error caused by the power difference, and this enables more highly accurate channel estimation. In the example as shown in Fig. 14, six pilot blocks are generated from pilot symbols belonging to seven different slots.

It is not necessary, when obtaining the channel estimation value of the n -th data symbol, to generate the same number of pilot blocks before and after the n -th pilot symbol as in the example of Fig. 3. Thus, the pilot block can also be generated only from the pilot symbols with the number less than (previous to) the n -th pilot symbol, considering the delay of the channel estimation.

The length of the pilot block can be determined regardless of the length of the slot. In addition, the length of the pilot block can be set equal to the length of the pilot symbol. In other words, the pilot block can consist of one pilot symbol. Furthermore, the length of the pilot block may be variable for each pilot block.

Through steps S1305-S1307, the channel estimation value acquisition section 1221 obtains the channel estimation values of the data symbols and pilot symbols. First, at step S1305, it obtains the pilot block average value $\bar{\xi}$ by averaging the pilot symbols $\hat{\xi}$ (estimated complex fading envelopes) contained in the pilot block. It repeats the processing for all the pilot blocks (step S1306). If the pilot block consists of a single pilot symbol, that pilot symbol $\hat{\xi}$ itself becomes the pilot block average value $\bar{\xi}$. In the example of Fig. 14, the pilot block average values $\bar{\xi}(n_i)$ are obtained for respective i-th pilot blocks, where i varies from -L to L and $i \neq 0$.

At step S1307, the channel estimation value $\tilde{\xi}$ of the data symbol or pilot symbol is obtained by calculating the weighted sum of the pilot block average values $\bar{\xi}$. In the example of Fig. 14, the channel estimation value $\tilde{\xi}(n)$ of the n-th data symbol is obtained by setting the weighting factors of the i-th pilot blocks as α_i .

In addition, in the present embodiment, the channel estimation values are also obtained for the pilot symbols to carry out the weighting control.

As the channel estimation value of the n-th pilot

symbol, the channel estimation value $\tilde{\xi}(n)$ of the n-th data symbol values can be used without any change.

The channel estimation value $\tilde{\xi}(n)$ is given by
5 the following equation (3).

$$\tilde{\xi}(n) = \sum_{i=-L, i \neq 0}^L \alpha_i \cdot \tilde{\xi}(n_i) \quad (3)$$

The foregoing steps S1304-S1307 are repeated for
10 all data symbols and pilot symbols with which the channel estimation values are to be obtained (step S1308).

After obtaining the channel estimation values, the data symbol sequence compensator 1230
15 compensates for the channel fluctuations of the data symbol sequence at step S1309 using the channel estimation values $\tilde{\xi}$ (of the data symbols). More specifically, it compensates for the channel fluctuations of the data symbols by multiplying the
20 data symbol sequence by the complex conjugates of the channel estimation values $\tilde{\xi}$.

At step S1310, the RAKE combiner 1232 carries out the coherent combining of the compensated data symbol sequences supplied from the RAKE fingers.

The CDMA receiver 1200 of the present embodiment carries out the same processing as the weighting control processing (Fig. 4) by the CDMA receiver 100 in the first embodiment in accordance with the present invention. In other words, the pilot symbol sequence compensator 1246 compensates for the channel fluctuations of the pilot symbol sequence at step S401 using the channel estimation values $\tilde{\xi}$ (of the pilot symbols).

At step S402, the error signal generator 1242 generates an error signal (identification error information) from the compensated pilot symbol sequence and the ideal pilot symbol sequence (which is not affected by the channel fluctuations). The ideal pilot symbol sequence is known, and is prepared in the receiver 1200 in advance.

At step S403, the weighting controller (MMSE) 1244 carries out the control of the weighting (weighting factors α_i) using the error signal and the pilot block average values (channel estimation values obtained from the individual pilot blocks) $\bar{\xi}_k$ as the feedback information.

Thus adaptively optimizing the weighting values for the pilot symbols in response to the channel fluctuation rate makes it possible to improve the

resistance to fading fluctuations, and to carry out the highly accurate channel estimation.

[SIXTH EMBODIMENT]

5 Fig. 15 is a block diagram showing a configuration of the CDMA transceiver of a sixth embodiment in accordance with the present invention. The CDMA transceiver 1500 of the present embodiment transmits a signal including a data symbol sequence and a pilot symbol sequence parallel to the data
10 symbol sequence, and receives and demodulates such a signal.

 The CDMA transceiver 1500 comprises a transmitting processor 1510 and a receiving
15 processor 1520. The configuration of the receiving processor 1520 and its receiving processing and weighting control processing are the same as the configuration (see, Fig. 12), the receiving processing (see, Figs. 13A and 13B) and weighting
20 control processing (see, Fig. 4) of the CDMA receiver 1200 of the fifth embodiment in accordance with the present invention.

 Fig. 16 is a block diagram showing a configuration of the transmitting processor of the
25 CDMA transceiver of the present embodiment. As shown in Fig. 16, the transmitting processor 1510

comprises a transmitting section 1610, a channel encoder 1622, a data symbol sequence spreader 1626, a pilot symbol sequence spreader 1628, and a combiner 1630. Although in the present embodiment, the channel encoder 1622, data symbol sequence spreader 1626 and the like are implemented by software using a DSP (plus a memory for storing programs) 1620, they can be implemented by means of hardware.

Fig. 17 is a flowchart illustrating a transmission processing by the transmitting processor of the CDMA transceiver of the present embodiment. First, at step S1701, the channel encoder 1622 generates a data symbol sequence by modulating (encoding) a data sequence. At step S1702, the data symbol sequence spreader 1626 generates a spread data symbol sequence by spreading the data symbol sequence using a first spreading code. At step S1703, the pilot symbol sequence spreader 1628 generates a spread pilot symbol sequence by spreading the pilot symbol sequence using a second spreading code. At step S1704, the combiner 1630 combines the spread data symbol sequence and the spread pilot symbol sequence, thereby generating a transmitted signal. At step

S1705, the transmitting section 1610 transmits the transmitted signal.

The present embodiment employs the first spreading code and second spreading code which are
5 orthogonal to each other. However, the first and second spreading codes can be used which are not orthogonal to each other.

In addition, the present embodiment combines a first carrier and a second carrier which are
10 orthogonal to each other after impressing the spread data symbol sequence and the spread pilot symbol sequence on the carries, and transmits the combined carrier. However, first and second carriers which are not orthogonal to each other can be combined
15 after impressing the spread data symbol sequence and spread pilot symbol sequence thereon, so as to be transmitted as the combined carrier.

[SEVENTH EMBODIMENT]

20 Fig. 18 is a block diagram showing a configuration of the CDMA receiver of a seventh embodiment in accordance with the present invention. The CDMA receiver 1800 of the present embodiment receives and demodulates a signal including a data
25 symbol sequence and a pilot symbol sequence parallel to the data symbol sequence.

The CDMA receiver 1800 comprises a receiving section 1810, a data symbol sequence matched filter 1824, a pilot symbol sequence matched filter 1826, a pilot block generator 1811, a channel estimation value acquisition section 1821, a data symbol sequence compensator 1830, a RAKE combiner 1832, a data decision section 1846, an error signal generator 1842, and a weighting controller (MMSE) 1844. Although in the present embodiment, the data symbol sequence matched filter 1824, pilot symbol sequence matched filter 1826 and the like are implemented by software using a DSP (plus a memory for storing programs) 1820 as shown in Fig. 18, they can also be implemented by means of hardware. The receiving section 1810, data symbol sequence matched filter 1824 and the like have the same configurations and functions as those of their counterparts of the CDMA receiver 1200 of the fifth embodiment in accordance with the present invention. In addition, the CDMA receiver 1800 of the present embodiment carries out the same processing as the receiving processing of the CDMA receiver 1200 (see, Fig. 13A and 13B) of the fifth embodiment in accordance with the present invention, except that it is unnecessary for the present embodiment to

obtain the channel estimation values of the pilot symbols.

Furthermore, the CDMA receiver 1800 of the present embodiment carries out the same processing
5 as the weighting control processing of the CDMA receiver 800 (see, Fig. 9) of the third embodiment in accordance with the present invention. Specifically, at step S901, the error signal generator 1842 generates an error signal
10 (identification error information) from the compensated data symbol sequence and from the result obtained by demodulating and deciding the compensated data symbol sequence. The data decision is carried out by the data decision section 1846
15 that makes a decision (0/1) of the output of the RAKE combiner 1832.

At step S902, the weighting controller (MMSE) 1844 carries out the control of the weighting (weighting factors α_i) using the error signal and
20 pilot block average values (channel estimation values obtained from the individual pilot blocks) \hat{h}_k as the feedback information.

Thus adaptively optimizing the weighting values
25 for the pilot symbols in response to the channel

fluctuation rate makes it possible to improve the resistance to fading fluctuations, and to carry out the highly accurate channel estimation.

Incidentally, a CDMA transceiver can be arranged
5 by employing the CDMA receiver 1800 of the seventh embodiment in accordance with the present invention as the receiving processor, and the transmitting processor 1510 of the CDMA transceiver 1500 of the sixth embodiment in accordance with the present
10 invention as the transmitting processor.

[EIGHTH EMBODIMENT]

Fig. 19 is a block diagram showing a configuration of a CDMA receiver of an eighth
15 embodiment in accordance with the present invention. The CDMA receiver 1900 of the present embodiment receives and demodulates a data symbol sequence and a pilot symbol sequence parallel to the data symbol sequence.

20 The CDMA receiver 1900 comprises a receiving section 1910, a data symbol sequence matched filter 1924, a pilot symbol sequence matched filter 1926, a pilot block generator 1911, a channel estimation value acquisition section 1921, a data symbol
25 sequence compensator 1930, a RAKE combiner 1932, and a weighting controller (inner product calculation)

1944. Although in the present embodiment, the data symbol sequence matched filter 1924, pilot symbol sequence matched filter 1926 and the like are implemented by software using a DSP (plus a memory for storing programs) 1920 as shown in Fig. 19, they can be implemented by means of hardware. The receiving section 1910, data symbol sequence matched filter 1924 and the like have the same configurations and functions as their counterparts of the CDMA receiver 1200 of the fifth embodiment in accordance with the present invention. Besides, the CDMA receiver 1900 of the present embodiment carries out the same receiving processing as the CDMA receiver 1200 (see, Figs. 13A and 13B) of the fifth embodiment in accordance with the present invention, except that it is unnecessary for the present embodiment to obtain the channel estimation values of the pilot symbols.

Furthermore, the CDMA receiver 1900 of the present embodiment carries out the same weighting control processing as the CDMA receiver 1000 (see, Fig. 11) of the fourth embodiment in accordance with the present invention. Specifically, at step S1101, the weighting controller (inner product calculation) 1944 carries out the control (updating) of the weighting (weighting factors α_i) using the inner

products (correlation values) of the channel estimation values $\tilde{\xi}$ of the data symbols values and the pilot block average values (channel estimation values obtained from individual pilot blocks) $\bar{\xi}$ as
5 the updating values (feedback information) as expressed by the following equation (4).

$$\left. \begin{aligned} \mathbf{A}(n) &= \mathbf{A}(n-1) + \mu \tilde{\xi}(n) \bar{\mathbf{X}}(n) \\ \mathbf{A}(n) &= \begin{pmatrix} \alpha_{-L}(n) \\ \vdots \\ \alpha_{-1}(n) \\ \alpha_1(n) \\ \vdots \\ \alpha_L(n) \end{pmatrix}, \quad \bar{\mathbf{X}}(n) = \begin{pmatrix} \bar{\xi}(n_{-L}) \\ \vdots \\ \bar{\xi}(n_{-1}) \\ \bar{\xi}(n_1) \\ \vdots \\ \bar{\xi}(n_L) \end{pmatrix} \\ \tilde{\xi}(n) &= \mathbf{A}^t(n-1) \cdot \bar{\mathbf{X}}(n) \end{aligned} \right\} (4)$$

10 where, $\mathbf{A}(n)$ is the weighting factor of the n -th data symbol, μ is a step size of the updating, $\bar{\xi}(n_i)$ is the pilot block average value of the i -th pilot block, and $\tilde{\xi}(n)$ is the channel estimation value of

the n-th data symbol. In addition, $A^t(n)$ denotes the transpose of $A(n)$.

Thus adaptively optimizing the weighting values for the pilot symbols in response to the channel fluctuation rate makes it possible to improve the resistance to fading fluctuations, and to carry out the highly accurate channel estimation.

Furthermore, it is unnecessary for the present embodiment to demodulate the data or to generate the error signal, which makes it possible to carry out the weighting control in response to the channel fluctuations with a simple configuration.

Incidentally, a CDMA transceiver can be configured by employing the CDMA receiver 1900 of the eighth embodiment in accordance with the present invention as the receiving processor, and the transmitting processor 1510 of the CDMA transceiver 1500 of the sixth embodiment in accordance with the present invention as the transmitting processor.

20

[SUPPLEMENTS]

Fig. 20 is a diagram illustrating characteristics of a required error rate ($BER=10^{-3}$) versus the product of a maximum Doppler frequency (f_d) and a slot time (T_{slot}) under a two-path

25

Rayleigh model. Fig. 20 illustrates characteristics (TM_P) associated with the CDMA receiver of the fourth embodiment in accordance with the present invention (time multiplexed pilot channel method),
5 characteristics (Para_P) associated with the CDMA receiver of the eighth embodiment in accordance with the present invention (parallel pilot channel method), characteristics (TM_C) associated with the conventional CDMA receiver with the fixed weighting factors (time multiplexed pilot channel method), and
10 characteristics (Para_C) associated with the conventional CDMA receiver with the fixed weighting factors (parallel pilot channel method).

Fig. 21 is a diagram illustrating BER
15 characteristics under a Vehicular-B environment when $f_d T_{s\text{slot}} = 0.003125$ and $f_d T_{s\text{slot}} = 0.28$, and Fig. 22 is a diagram illustrating characteristics of a required error rate ($\text{BER} = 10^{-3}$) versus $f_d T_{s\text{slot}}$ under the Vehicular-B environment.

20 It is found from Figs. 20 and 22 that both the CDMA receivers of the fourth and eighth embodiments in accordance with the present invention have an improvement of about 0.2 dB under the two-path Rayleigh model and of about 0.4 dB under the
25 Vehicular-B environment in a low rate fading as compared with the conventional CDMA receiver, and

that the improvement increases with the fading rate in a high rate fading. Here, the improvement under the Vehicular-B environment is greater than that under the two-path Rayleigh model low rate fading
5 because the present invention has a greater improvement when it can use more pilot symbols as in the Vehicular-B environment in which the effect of noise is greater during the low fading.

Furthermore, it is thought that the time
10 multiplexed pilot channel method (the CDMA receiver of the fourth embodiment in accordance with the present invention) and the parallel pilot channel method (the CDMA receiver of the eighth embodiment in accordance with the present invention) have
15 little difference over the entire range from the low rate to high rate fading. This is because in the low rate, the energy used for the estimation is equal, and the fading fluctuations are small, and because in the high rate, the effect characteristic
20 of the time multiplexed pilot channel method that the signal energy is obtained in a short time is nearly comparable to the improvement of the parallel pilot channel method in the traceability to the high rating fading owing to a reduction in the number of
25 synchronization additions of the parallel pilot

channel method as compared with the time multiplexed pilot channel method.

As described above, the present invention can improve the resistance to fading fluctuations and
5 carry out the highly accurate channel estimation by adaptively optimizing the weighting values for the pilot symbols in response to the rate of channel fluctuations.

Achieving the highly accurate channel estimation
10 and the compensation for the channel fluctuations of the data symbols based on the estimation makes it possible to implement the absolute phase decision for each data symbol using the coherent detection even under the Rayleigh fading environment, for
15 example, and hence to reduce the SNIR required for obtaining a required reception quality (received error rate). This can reduce the transmission power and increase the capacity of the system in terms of the number of users.

WHAT IS CLAIMED IS:

1. A CDMA receiver for receiving and demodulating a signal including a combined symbol sequence that has
5 a plurality of slots and includes data symbols and pilot symbols, said CDMA receiver comprising:

means for detecting positions of the pilot symbols in the combined symbol sequence;

10 means for generating pilot blocks by extracting in a plurality of slots the pilot symbols from the combined symbol sequence in response to a result of the detection;

means for obtaining channel estimation values by calculating a weighted sum of average values of the
15 pilot symbols in the pilot blocks;

means for acquiring from the combined symbol sequence a data symbol sequence in accordance with the result of the detection;

20 means for compensating for channel fluctuations of the data symbol sequence using the channel estimation values; and

means for controlling the weighting in response to a rate of the channel fluctuations.

25 2. The CDMA receiver as claimed in claim 1, wherein said means for controlling the weighting comprises:

means for compensating for, using the channel estimation values, channel fluctuations of a pilot symbol sequence extracted from the combined symbol sequence;

5 means for generating an error signal from the compensated pilot symbol sequence and an ideal pilot symbol sequence; and

means for carrying out the weighting control using the error signal and the average values of the
10 pilot symbols included in the pilot blocks.

3. The CDMA receiver as claimed in claim 1, wherein said means for controlling the weighting comprises:

means for generating an error signal from the
15 compensated data symbol sequence and from result obtained by demodulating and deciding the compensated data symbol sequence; and

means for carrying out the weighting control using the error signal and the average values of the
20 pilot symbols included in the pilot blocks.

4. The CDMA receiver as claimed in claim 1, wherein said means for controlling the weighting carries out the weighting control using as update values inner
25 products of the channel estimation values of the

data symbols and the average values of the pilot symbols included in the pilot blocks.

5. The CDMA receiver as claimed in any one of
5 claims 1-4, wherein said CDMA receiver receives a signal including a combined symbol sequence having a frame structure consisting of slots in which the pilot symbols consisting of a few symbols are inserted into the data symbol sequence at every
10 fixed interval.

6. The CDMA receiver as claimed in any one of
claims 1-5, wherein the pilot blocks are formed from
15 all the pilot symbols in a slot.

7. The CDMA receiver as claimed in any one of
claims 1-6, wherein when obtaining the channel
estimation value of a data symbol in an n -th slot of
the combined symbol sequence, where n is an integer,
20 the pilot blocks are generated from an $(n-K+1)$ -th slot to an $(n+K)$ -th slot of the combined symbol sequence, where K is a natural number.

8. A CDMA receiver for receiving and demodulating a
25 signal including a data symbol sequence and a pilot

symbol sequence parallel to the data symbol
sequence, said CDMA receiver comprising:

means for generating a plurality of pilot blocks
from the pilot symbol sequence;

5 means for obtaining channel estimation values by
calculating a weighted sum of average values of the
pilot symbols in the pilot blocks;

means for compensating for channel fluctuations
of the data symbol sequence using the channel
10 estimation values; and

means for controlling the weighting in response
to a rate of the channel fluctuations.

9. The CDMA receiver as claimed in claim 8, wherein
15 said means for controlling the weighting comprises:

means for compensating for, using the channel
estimation values, channel fluctuations of the pilot
symbol sequence;

means for generating an error signal from the
20 compensated pilot symbol sequence and an ideal pilot
symbol sequence; and

means for carrying out the weighting control
using the error signal and the average values of the
pilot symbols included in the pilot blocks.

25

10. The CDMA receiver as claimed in claim 8,
wherein said means for controlling the weighting
comprises:

means for generating an error signal from the
5 compensated data symbol sequence and from result
obtained by demodulating and deciding the
compensated data symbol sequence; and

means for carrying out the weighting control
using the error signal and the average values of the
10 pilot symbols included in the pilot blocks.

11. The CDMA receiver as claimed in claim 8,
wherein said means for controlling the weighting
carries out the weighting control using as update
15 values inner products of the channel estimation
values of the data symbols and the average values of
the pilot symbols included in the pilot blocks.

12. The CDMA receiver as claimed in any one of
20 claims 8-11, wherein said CDMA receiver receives a
signal including a data symbol sequence which is
spread using a first spreading code, and a pilot
symbol sequence which is parallel to the data symbol
sequence and spread using a second spreading code,
25 the first spreading code and the second spreading
code being orthogonal to each other.

13. The CDMA receiver as claimed in any one of claims 8-12, wherein said CDMA receiver receives a signal including a spread data symbol sequence which is impressed on a first carrier, and a spread pilot symbol sequence which is parallel to the data symbol sequence and is impressed on a second carrier, the first carrier and the second carrier being orthogonal to each other.

14. The CDMA receiver as claimed in any one of claims 8-13, wherein when obtaining the channel estimation value of an n -th data symbol in the data symbol sequence, where n is an integer, the plurality of pilot blocks are generated from an $(n-K+1)$ -th pilot symbol to an $(n+K)$ -th pilot symbol in the pilot symbol sequence, where K is a natural number.

15. The CDMA receiver as claimed in any one of claims 8-14, wherein the plurality of pilot blocks have a same length.

16. A CDMA transceiver including a transmitting section for transmitting a signal including a combined symbol sequence that has a plurality of

slots and includes data symbols and pilot symbols,
and a receiving section for receiving and
demodulating the signal, said receiving section
comprising:

5 means for detecting positions of the pilot
symbols in the combined symbol sequence;

 means for generating pilot blocks by extracting,
in a plurality of slots, the pilot symbols from the
combined symbol sequence in response to a result of
10 the detection;

 means for obtaining channel estimation values by
calculating a weighted sum of average values of the
pilot symbols included in the pilot blocks;

 means for acquiring from the combined symbol
15 sequence a data symbol sequence in accordance with
the result of the detection;

 means for compensating for channel fluctuations
of the data symbol sequence using the channel
estimation values; and

20 means for controlling the weighting in response
to a rate of the channel fluctuations.

17. A CDMA transceiver including a transmitting
section for transmitting a signal including a data
25 symbol sequence and a pilot symbol sequence parallel
to the data symbol sequence, and a receiving section

for receiving and demodulating the signal, said receiving section comprising:

means for generating a plurality of pilot blocks from the pilot symbol sequence;

5 means for obtaining channel estimation values by calculating a weighted sum of average values of the pilot symbols in the pilot blocks;

means for compensating for channel fluctuations of the data symbol sequence using the channel
10 estimation values; and

means for controlling the weighting in response to a rate of the channel fluctuations.

18. A CDMA receiving method of receiving and
15 demodulating a signal including a combined symbol sequence that has a plurality of slots and includes data symbols and pilot symbols, said CDMA receiving method comprising the steps of:

detecting positions of the pilot symbols in the
20 combined symbol sequence;

generating pilot blocks by extracting, in a plurality of slots, the pilot symbols from the combined symbol sequence in response to a result of the detection;

obtaining channel estimation values by
calculating a weighted sum of average values of the
pilot symbols in the pilot blocks;

acquiring from the combined symbol sequence a
5 data symbol sequence in accordance with the result
of the detection; and

compensating for channel fluctuations of the
data symbol sequence using the channel estimation
value,

10 wherein the weighting is controlled in response
to a rate of the channel fluctuations.

19. A CDMA receiving method of receiving and
demodulating a signal including a data symbol
15 sequence and a pilot symbol sequence parallel to the
data symbol sequence, said CDMA receiving method
comprising the steps of:

generating a plurality of pilot blocks from the
pilot symbol sequence;

20 obtaining channel estimation values by
calculating a weighted sum of average values of the
pilot symbols in the pilot blocks; and

compensating for channel fluctuations of the
data symbol sequence using the channel estimation
25 value,

wherein the weighting is controlled in response to a rate of the channel fluctuations.

ABSTRACT OF THE DISCLOSURE

A CDMA receiver and a CDMA transceiver are provided which have high resistance to fading
5 fluctuations, and carry out highly accurate channel estimation, considering the rate of channel fluctuations. When carrying out the channel estimation by calculating weighted sums of the (average values of) pilot symbols interposed into a
10 data symbol sequence, the weighting control is performed considering the rate of the channel fluctuations. For example, the weighting control is carried out using, as its update values, inner products of the channel estimation values and the
15 (average values of) pilot symbols. This makes it possible to achieve the highly accurate channel estimation.








FIG.1


FIG.2




**FIG.2B**

CHANNEL ESTIMATION VALUE OF m -TH DATA SYMBOL OF n -TH SLOT**FIG.3**


5/25

**FIG.4**


6/25

**FIG.5**

7/25

**FIG.6**

8/25

**FIG.7**

9/25





FIG.8

10/25

**FIG.9**





FIG. 10

12/25

**FIG.11**

13/25








FIG.12

14/25

FIG.13




**FIG.13B**




CHANNEL ESTIMATION VALUE OF n -TH DATA SYMBOL

FIG.14


17/25

**FIG.15**

18/25

**FIG.16**

19/25

**FIG.17**

20/25




FIG.18






FIG. 19

22/25

**FIG.20**

23/25

**FIG.21**

24/25





FIG.22

**FIG. 23**CHANNEL ESTIMATION VALUE COMMON TO DATA SYMBOLS IN n -TH SLOT

**DECLARATION AND POWER OF ATTORNEY
for patent application**

(COMPLETE IF KNOWN)

Application Number		Attorney Docket Number	
Filing Date		First Named Inventor	ABETA
Group Art Unit			
Examiner			

This declaration is (*check one*):

- ☒ submitted with initial filing;
☐ submitted after initial filing;
☐ a supplemental declaration.

This application is of the following type:

- ☒ utility;
☐ design;
☐ national stage of PCT;
☐ divisional, continuation or
continuation-in-part.

As a below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (*if only one name is listed below*) or an original, first and joint inventor (*if plural names are listed below*) of the subject matter which is claimed and for which a patent is sought on the invention entitled:

CDMA RECEIVER AND CDMA TRASCEIVER

the specification of which: (*check one*)

- ☒ is attached hereto; or
☐ was filed on _____ as U.S. Application No. _____ and is/was amended on _____ (*if applicable*);
☐ was described and claimed in PCT International Application No. _____, filed on _____ and was amended under PCT Article 19 on _____ (*if applicable*).

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, §1.56.

I hereby identify below, and where indicated claim foreign priority benefits under Title 35, United States Code §§ 119(a)-(d) or §§ 365(a)-(b) of any foreign application(s) for patent or inventor's certificate or of any PCT international application(s) designating at least one country other than the United States of America, filed within 12 months (6 months for design) prior to this application, and have also identified below any foreign application(s) for patent or inventor's certificate or any PCT international application(s) designating at least one country other than the United States of America filed by me on the same subject matter having a filing date before that of the application(s) on which priority is claimed (*if any*):

Foreign/PCT Application Number	Country	Filing Date (MM/DD/YYYY)	Priority Claimed	
113581/1998	Japan	April 23, 1998	(x)Yes	()No
			()Yes	()No
			()Yes	()No

I hereby claim the benefit under Title 35, United States Code, §119(e) of any United States provisional application(s) listed below (if any):

Provisional Application No.	Filing Date

I hereby claim the benefit under Title 35, United States Code, § 120 of any United States application(s), or § 365(c) of any PCT International Application designating the United States of America listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT international application in the manner provided by the first paragraph of Title 35, United States Code, § 112, I acknowledge the duty to disclose information which is material to patentability as defined in Title 37, Code of Federal Regulations, § 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application:

U.S./PCT Parent Application No.	Filing Date	Status (<i>Patented, Pending, or Abandoned</i>)
PCT/JP99/02154	April 22, 1999	Pending

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

As a named inventor, I hereby appoint the following attorney(s) or agent(s) with full power of substitution and revocation to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:

Seth H. Ostrow, Reg. No. 37,410
 Larry Liberchuk, Reg. No. 40,352

Louis J. Greco, Reg. No. 41,799
 Anthony J. Natoli, Reg. No. 36,223

Direct all correspondence to:

Brown Raysman Millstein Felder & Steiner LLP
120 West 45th Street
New York, New York 10036

Direct all telephone calls to: (212) 944-1515

Full Name of Sole or First Inventor		<u>Sadayuki ABETA</u>	
Inventor's Signature	<u>Sadayuki Abeta</u>	Date	December 15, 1999
Residence	<u>Kanagawa, Japan J P X</u>	Citizenship	Japan
Post Office Address	4-18-4-102, Nobi, Yokosuka-shi, Kanagawa 239-0841, JAPAN		

(check one) Sheets containing additional joint inventors (x) are, () are not attached hereto.

2-8

Full Name of Second Joint Inventor		<u>Mamoru SAWAHASHI</u>	
Inventor's Signature	<i>Mamoru Sawahashi</i>	Date	December 15, 1999
Residence	<u>Kanagawa, Japan</u> □ □ ×	Citizenship	Japan
Post Office Address	1-59-17, Tomiokanishi, Kanazawa-ku, Yokohama-shi, Kanagawa 236-0052, JAPAN		

2-9

Full Name of Third Joint Inventor		<u>Fumiyuki ADACHI</u>	
Inventor's Signature	<i>Fumiyuki Adachi</i>	Date	December 15, 1999
Residence	<u>Kanagawa, Japan</u> □ □ ×	Citizenship	Japan
Post Office Address	6-12-4, Tomiokanishi, Kanazawa-ku, Yokohama-shi, Kanagawa 236-0052, JAPAN		